Hướng Dẫn Cấu Hình VPN Mikrotik

1. <u>Cấu hình VPN Server</u>

Bước 1: Bật tính năng PTPP Server

Vào PPP ->Interface -> chọn vào PTPP Server,

A Quick Set												
Wireless	Interface		DeE Convers	Coord	ata Dra	files Acti	vo Connoct	iona				
🛲 Interfaces		PP	POE Servers	Secre	ets Pro	files Acti	ve Connect	ions				
🕌 Bridge	Add Nov		DDD Separat	DDTD	Server	CCTD Con			DDDoE Con			
🛫 Switch	Additiev	v •	FFF Scalifier		Server	331F 361V						
📑 PPP	2 items											
°t <mark>°</mark> Mesh	_				_			_	_			• • • • •
🖉 MPLS 🔹 🕨			▲ Name		Туре		L2 MTU	Tx .	Rx 120 B like	_	Tx Packet (p/s)	Rx Packet (p/s)
255 IP 🕨	- 0	ĸ	«» pppoe-ou	+2	PPPOE CI	ent		2.5 Mbps	139.3 KDp	S	239	138
🚜 Routing 🕨 🕨	-	^	** pppoe-ou	12 1	FFFOL CI	SIIL		0 Dps	0 Dps		U	0
top System ►	-											
Queues	-											
	-											
Radius	-											
New Terminal	-											
Tools	-											
· · · · · ·	-											
	کی کرد کے Wi آست In	uick S ireles: terfac	et s									
	کی ور ۱۳۳۶ In ۱۳۳۶ Br	uick S ireles: terfac idge	et s es		OK	Cancel	Apply					
	کی ور ک W اس In کی Br کی Br	uick S ireless terfac idge witch	et s es		ок (Cancel	Apply					
	کے لاہ ایس In کی Br کی Br کی PP	uick S ireles: terfac idge witch	et s es		ок [Cancel	Apply					
	کی ور ک W ایس In کی Br کی Br کی PF در Ma	uick S ireless terfac idge witch PP esh	et s es		ок [Cancel	Apply					
	Cu Cu Cu Cu Cu Cu Cu Cu Cu Cu Cu Cu Cu C	uick S ireless terfac idge witch PP esh PLS	et		ок [Cancel Ena Max	Apply abled MTU	✓				
	کی ور کے W کے W کی Br کی Br کی Br C Me C Me C Me E IP	uick S ireless terfac idge witch PP esh PLS	et es es		ок (Cancel Ena Max	Apply abled MTU	✓				
	Image: Constraint of the second s	uick S ireless terfac idge witch PP esh PLS	et es •		ок (Cancel Enz Max Max	Apply abled MTU MRU	 ✓ 1450 1450 				
	Image: Constraint of the second s	uick S ireless iterfac idge witch PLS PLS puting	et es ••••••••••••••••••••••••••••••••••		ок (Cancel Ena Max Max	Apply abled MTU MRU	 ✓ 1450 1450 				
	Image: Constraint of the second s	uick S ireles: iterfac ridge witch PP S outing vstem ueues	et es ••••••••••••••••••••••••••••••••••		ок (Cancel Ena Max Max	Apply bled MTU MRU	 ✓ 1450 1450 				
	Image: Constraint of the second s	uick S ireles: terfac vidge witch PP esh PLS outing vstem ses	et s es ••••••••••••••••••••••••••••••••		ок	Cancel Ena Max Max Max	Apply bled MTU MRU IRRU	 ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ 				
	Image: Constraint of the second s	uick S ireless tterfac witch PP ssh PLS ystem ueues les pg	et		ок (Cancel Ena Max Max Max Max	Apply bled MTU MRU IRRU	 ✓ ✓ ✓ ✓ ✓ ✓ 				
	Image: Constraint of the second s	uick S ireles: terfac ridge witch PLS p buting vstem ueues les yg adius	et		ок Кеер С	Cancel Enz Max Max Max Max Palive Tim	Apply bled MTU MRU IRRU rofile	 ✓ ✓				
	Image: Constraint of the second s	uick S ireles: terface witch PP esh PLS outing ueues les les les eg adius	at es b b b c minal		OK (Cancel Enz Max Max Max Max Palive Tim	Apply abled MTU MRU IRRU rofile	 ✓ 1450 1450 ✓ 30 default ✓ mschap2 	▼			
	C Qu C W Im In St Br St PF St Me P P Me P P P P P P P P P P P P P	uick S ireles: terfac idge witch PP esh PLS outing vstem ueues les og adius ew Ter pols	es		OK Keep C	Cancel Enz Max Max Max Palive Tim pefault Pr uthentic	Apply Abled MTU MRU IRRU isout ation	 ✓ 1450 1450 √ 30 default ✓ mschap2 ✓ chap 	▼ w mschap1 w pap			
	A Qui Constant Qui Constan	uick S ireless terfac idge witch PPS outing vstem ueues les les es dus ew Ter pols	et es es es es es es es es es es es es es		OK Keep C	Cancel Enz Max Max Max Palive Tim befault Pr uthentica	Apply abled MTU MRU IRRU Fofile	 ✓ 1450 1450 ✓ 30 default ✓ mschap2 ✓ chap 	▼ w mschap1 w pap			

Bước 2: Cấu hình VPN

Đầu tiên tạo một dãi IP Pool cấp cho các Client truy cập VPN. Vào Pool -> Add New,

Wireless					
Interfaces	Pools Us	ed Addresses			
Bridge					
w Switch	Add New				
	4 items				
15 Mesh		A Name	Addresses	Next Pool	
MPLS •		≜ default-dbco	192 168 88 10-192 168 88 254	none	
ip T			102 169 100 10 102 169 100 140	none	
ARP		+ dhep_pool1	192.168.100.10-192.108.100.149	none	
Accounting		+ dhep_pool2	192.168.30.2.192.168.30.254	none	
Addresses		- ancp_poors	192.168.20.2-192.168.20.254	none	
Cloud					
DHCP Client					
DHCP Relay					
DHCP Server					
DNS					
Firewall					
Hotspot					
IPsec					
Neighbors					
Packing					
Packing Pool					
Packing Pool Routes dãi IP sẽ cấ	p cho các	thiết bị Clien	it,		
Packing Pool Routes dãi IP sẽ cấ	p cho các	thiết bị Clier	u, TI	n	
Packing Pool Routes dãi IP sẽ cấ Quick Set Wireless	p cho các	thiết bị Clier	it,	n	
Packing Pool Routes dãi IP sẽ cấ Quick Set Wireless Interfaces Stridge	p cho các	thiết bị Clier	it,	n	
Packing Pool Routes dãi IP sẽ cấ Quick Set Wireless Interfaces Bridge Switch	р cho các	thiết bị Clien	it,	n	
Packing Pool Routes dãi IP sẽ cấ Quick Set Vireless Interfaces Stridge Switch PPP	р cho các ок Сапсе	thiết bị Clien		h	
Packing Pool Routes dãi IP sẽ cấ Quick Set Wireless Interfaces Bridge Switch PPP % Mesh	р cho các ок Сапсе Name	thiết bị Clien	it, 1		
Packing Pool Routes dãi IP sẽ cấ Quick Set Wireless Interfaces Bridge Switch PPP Switch MPLS MPLS	p cho các OK Cance Name Addresses	 thiết bị Clien Apply pool-vpn 10.0.0.2-10.0.0.254 			
Packing Pool Routes dãi IP sẽ cấ Quick Set I Wireless Interfaces Switch Switch PPP Switch PPP Switch MPLS POD	р cho các ок Cance Name Addresses	 thiết bị Clien Apply pool-vpn 10.0.0.210.0.0.254 	it,		
Packing Pool Routes dãi IP sẽ cấ Quick Set T Wireless Interfaces Switch Switch Switch PPP Switch MPLS PIP TP ARP	DK Cance OK Cance Name Addresses Next Pool	 thiết bị Clien Apply pool-vpn 10.0.0.210.0.0.254 none 	it,		
Packing Pool Routes dãi IP sẽ cấ Quick Set Wireless Interfaces Stidge Switch Switch Switch PPP Switch PPP MPLS ARP Accounting Addresses	DK Cance OK Cance Name Addresses Next Pool	 thiết bị Clien Apply pool-vpn 10.0.0.2-10.0.0.254 none 	it,		
Packing Pool Routes dãi IP sẽ cấ Quick Set Wireless Interfaces Bridge Switch Switch Switch Switch PPP MPLS ARP Accounting Addresses Cloud	p cho các OK Cance Name Addresses Next Pool	 thiết bị Clien Apply pool-vpn 10.0.0.2-10.0.0.254 none 	it,		
Packing Pool Routes dãi IP sẽ cấ [™] Quick Set [™] Wireless [™] Uireless [™] Interfaces [™] Bridge [™] Switch [™] Switch [™] Switch [™] PPP [™] Mesh [™] MPLS [™] ARP Accounting Addresses Cloud DHCP Client	p cho các OK Cance Name Addresses Next Pool	 thiết bị Clien Apply pool-vpn 10.0.0.2-10.0.0.254 none 	it,		
Packing Pool Routes Routes Routes Routes Routes Routes Cloud DHCP Client DHCP Relay	p cho các OK Cance Name Addresses Next Pool	thiết bị Client Apply pool-vpn 10.0.0.2-10.0.0.254 none	it,		
Packing Pool Routes Routes Routes Routes Routes Routes Cloud Cloud DHCP Client DHCP Relay DHCP Server	p cho các OK Cance Name Addresses Next Pool	thiết bị Client Apply pool-vpn 10.0.0.2-10.0.0.254 none			
Packing Pool Routes Routes Cai IP se cá Quick Set Wireless Fildge Switch Switch Switch PPP Switch PPP Switch PPP Switch PPP Composition ARP Accounting Addresses Cloud DHCP Client DHCP Server DNS	p cho các OK Cance Name Addresses Next Pool	thiết bị Client Apply pool-vpn 10.0.0.2-10.0.0.254 none			
Packing Pool Routes Routes Cai IP se cá Quick Set Wireless Firewall Accounting Addresses Cloud DHCP Client DHCP Relay DHCP Server DNS Firewall	p cho các OK Cance Name Addresses Next Pool	thiết bị Client Apply pool-vpn 10.0.0.2-10.0.0.254 none			
Packing Pool Routes Routes Cai IP se cá Quick Set Wireless Firewall Accounting Addresses Cloud DHCP Client DHCP Relay DHCP Server DNS Firewall Hotspot	p cho các OK Cance Name Addresses Next Pool	thiết bị Client Apply pool-vpn 10.0.0.2-10.0.0.254 none	t,		
Packing Pool Routes Cdãi IP sẽ cấ Cdãi IP số Cấ Cấ Cấ Cấ Cấ Cấ Cấ Cấ Cấ	p cho các OK Cance Name Addresses Next Pool	thiết bị Client Apply pool-vpn 10.0.0.2-10.0.0.254 none	t,		
Packing Pool Routes Cdãi IP sẽ cấ Quick Set ↓ Wireless Interfaces S Bridge Switch S Bridge Switch S Bridge Switch S Drige PPP Comparison ARP Accounting Addresses Cloud DHCP Client DHCP Relay DHCP Server DNS Firewall Hotspot IPsec Neighbors Packing	p cho các OK Cance Name Addresses Next Pool	thiết bị Client Apply pool-vpn 10.0.0.2-10.0.0.254 none	t,		

Tạo

Tiếp theo, vào PPP -> Profiles để khai báo một Profile VPN, chọn Add new,

http://www.com/com/com/com/com/com/com/com/com/com/									
🚊 Wireless	Interfac	-	PPoF Servers Se	ecrets Profiles	Active Conn	ections			
Interfaces	111001101	~ [.							
📲 Bridge	Add Ne								
🙄 Switch	Addine	··· .							
PPP	2 items								
°to Mesh	2 100110								
Ø MPLS			A Name	Local Address	Remote	Bridge	Rate	Only One	
255 IP 🔻				Local maaress	Address	bridge	(rx/tx)	only one	
ARP	-	*	🚷 default					default	
Accounting	-	*	🚱 default-encry					default	
Addresses									
Cloud									
DHCP Client									
DHCP Relay									
DHCP Server									

Khai báo Local Address và gán Remote Address là dãi IP Pool vừa tạo,

ouick Set 🌋	
🧘 Wireless	
🛲 Interfaces	
📲 🖁 Bridge	
🛫 Switch	
PPP	
°T <mark>8</mark> Mesh	
MPLS	
255 IP 🔻	Name pro-vpn
ARP	Local Address
Accounting	
Addresses	Remote Address 🔺 pool-vpn 🔻
Cloud	Define -
DHCP Client	bridge +
DHCP Relay	Bridge Port Priority
DHCP Server	
DNS	Bridge Path Cost 🔻
Firewall	Incoming Filter
Hotspot	
IPsec	Outgoing Filter 🔻
Neighbors	
Packing	Address List 🔻

Vào tab *Secrets* (trong PPP) tạo các tài khoản ppp user truy cập, đánh mật khẩu truy cập VPN và gán Profile VPN vào.

http://www.com/action/a	
🚊 Wireless	
Interfaces	
🕌 🖁 Bridge	
🛫 Switch	
PPP	
°t₀ Mesh	Enabled 🕑
MPLS	Name pppclient1
255 IP 🕨	
🎉 Routing 🛛 🕨	Password 123456
🛞 System 🕨	Coming Insta
🙊 Queues	service
Files	Caller ID 🔻
E Log	
🥵 Radius	Profile pro-vpn 🔻
📰 New Terminal	Local Address
💥 Tools 🔹 🕨	
🛃 MetaROUTER	Remote Address 🔻
🕭 Partition	
🔒 Make Supout.rif	Routes 🔻

2. Cấu hình truy cập VPN từ thiết bị Client

Tùy thuộc vào hệ điều hành của máy tính Client mà có hướng dẫn truy cập VPN khác nhau. Bài hướng dẫn này sử dụng một máy tính Window 7 để làm Client truy cập VPN từ xa:

Yêu cầu phải xác định được địa chỉ IP WAN của VPN Server.

Từ máy Client, vào Network and Sharing Center, chọn Set up a new connection or network,



Chọn vào Connect to Workplace và nhấn Next,

Choose a connection option	•
Set up a wireless, broadband, or dial-up connection to the Internet.	
Configure a new router or access point.	E
Connect to a workplace	
Set up a dial-up or VPN connection to your workplace.	
Connect to the Internet using a dial-up connection.	-
	Next Cancel
se my Internet connection (VPN),	

Đánh địa chỉ IP WAN của VPN Server vào mục Internet Address, chọn Next,

What is a VPN connection?

 Dial directly Connect directly to a phone number without going through the Internet.

Cancel

Click

🚱 🌆 Connect to a Workplace		
Type the Internet add	ress to connect to	
Your network administrator	can give you this address.	
Internet address:	113100010100	1
Destination name:	VPN Connection	
Use a smart card () In the people t This option allows a Don't connect now;	o use this connection nyone with access to this computer to use this connection. just set it up so I can connect later	
	Next	Cancel
110		

Tiếp theo đánh User name và Password truy cập và kết nối,

ĺ	📀 🔚 Connect to a Workpl	lace		
	Type your user na	me and password		
	User name:	pppclient1		
	Password:	•••••		
		Show characters Remember this password		
	Domain (optional):			
HOT				TIN
			Connect Cancel	

Trong trường hợp không kết nối được có thể chọn *Skip* bỏ qua để vẫn tạo ra một Network VPN cho máy Client. Sau đó vào kết nối lại và tùy chỉnh một số thông tin trong *Security*.

	Control Panel Vietw	Demonstration of	Delete this		2		
Organize	Start this connection	Rename this connection	Delete this connection	»		₽ ▼ □	
	Local Area Connection Network cable unplugged	VPN Connecte Disconnecte	d	Wirele VienTi	ess Network Connect in	tion	
× 👳 c	onnect VPN Connection	EX.	VPN Connection F	Properties			
			General Options	ecurity Networki	ing Sharing		
			Type of VPN:	- I (/DD)	TD)	_	
			Point to Point Tunn	eling Protocol (PP	(Advapped op	ttings	
			Data encryption:		Auvanceuse	aungs	
			No encryption allow	ved (server will disc	connect if it requires en	icry 🔻	
			O Use Extensible	Authentication Pro	otocol (EAP)		
Use	rname: pppclient i					~	
Pa	sword:				Propertie	es	
Do	nain:		 Allow these pro 	tocols			
	Save this user name and password	for the following users:					
	Me only Anyone who uses this compute	er.	Unencrypter	d password (PAP)	n n Bar Morris		
			V Challenge H	landshake Authen HAP Version 2 (MS	ication Protocol (CHA) GCHAP v2)	P)	
	Connect Cancel Pr	Properties Help	Automat	ically use my Wind	lows logon name and		
)	passion	a (ana aomain, ir a	, iy)		
					ОК С	ancel	
sau khi ka	ết nối thành côn	ng	~ 1				
sau khi ké	ết nối thành côi	ng	<u>11</u>				
sau khi ka	ết nối thành côi	ng	ר 1		n		e X
sau khi ka	Ét nối thành côn Control Panel • Network	ng	Connections >	• 47	Search Network C	Connections	0 X 2
sau khi ka	Ét nối thành cô: • Control Panel • Network Disconnect this connection	ng k and Internet Network (Rename this connect	Connections >	✓ 4→ (this connection	Search Network C	ionnections	ی ا م ا
sau khi ki	Ét nối thành côi Control Panel → Network Disconnect this connection ark cable unplugged	ng (and Internet) Network (n Rename this connect VPN Connect VPN Connect	Connections > tion View status of tion		Search Network Con	onnections	0 X 2 2 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3 3
sau khi ki Organize • Netw Realt	Ét nối thành côi Control Panel > Network Disconnect this connection Area Connection ork cable unplugged # PCIe GBE Family Controlle	ng and Internet Network (Rename this connect VPN Connect VPN Connect VPN Connect WAN Minippo	Connections > tion View status of tion tion rt (PPTP)	• • • • • • • • • • • • • • • • • • •	Search Network Co n >> reless Network Cor en Tin heros AR9485WB-E	ionnections	
sau khi ko Organize • Netw Realt	Ét nối thành côi Control Panel → Network Disconnect this connection ork cable unplugged k PCle GBE Family Controlle PN Connection Status	ng k and Internet Network (Rename this connect VPN C	Connections > tion View status of tion ntr (PPTP)	• 49 this connection Vie Ath	Search Network Co n » reless Network Cor n Tin neros AR9485WB-E	onnections	
sau khi ki Organize • Netw Realt	Ét nối thành côi Control Panel → Network Disconnect this connection ork cable unplugged sk PCIe GBE Family Controlle PN Connection Status teral Details	ng and Internet Network (Rename this connect VPN Connect VPN Connect WAN Minipo	Connections > tion View status of tion tion nt (PPTP) SZ Network Conr	• • • • • • • • • • • • • • • • • • •	Search Network Co n » reless Network Cor n Tin neros AR9485WB-E	onnections	
sau khi ki Organize • Netw Realt	Control Panel Network Control Panel Network Disconnect this connection ork cable unplugged k PCIe GBE Family Controlle PN Connection Status veral Details annection	ng k and Internet Network (n Rename this connect VPN Connec VPN Connec VPN Connec VPN Connec	Connections > tion View status of tion tion tri (PPTP) SS Network Conr Network Conr	+ +++ (this connection Vie Ath nection Details	Search Network Conn >> reless Network Cornn Tin neros AR9485WB-E	onnection G Wireless N	
sau khi ki	Ét nối thành côi Control Panel ► Network Disconnect this connection Ork cable unplugged sk PCIe GBE Family Controlle PN Connection Status Teral Details onnection IPv4 Connectivity:	ng and Internet Network (Rename this connect VPN Con	Connections > tion View status of tion tion tion str (PPTP) 23 Network Conr t Network Conr Property	+ +y (this connection Vie Ath nection Details	Search Network Conn >> reless Network Corn nTin neros AR9485WB-E	ionnections	
sau khi ki Organize • Netw Realt	Ét nối thành côi Control Panel → Network Disconnect this connection ork cable unplugged sk PCIe GBE Family Controlle PN Connection Status Peral Details sinnection IPv4 Connectivity: IPv6 Connectivity:	ng and Internet Network (Rename this connect VPN Con	Connections > tion View status of tion tion tion tion tion tion Property Connection s	+ +++ (this connection Vie Att nection Details specific DN	Search Network Co n » reless Network Cor nTin heros AR9485WB-E	onnections	
sau khi ki Organize • Netw Realt	Ét nối thành côi Control Panel → Network Disconnect this connection ork cable unplugged k PCle GBE Family Controlle PN Connection Status reral Details onnection IPv4 Connectivity: IPv6 Connectivity: Media State: Duration:	and Internet Network (Rename this connect VPN Connect VPN Connect VPN Connect Internet No network access Connecte Output	Connections ► tion View status of tion tion tion tr (PPTP) SS Network Connection Property Connection Property Connection Property Connection Property Connection Property Connection Property Connection Property Connection Property Connection Property Connection Property Connection Property Connection Property	• 4 (4) this connection win Vie Ath nection Details: specific DN dress	Search Network Connection	onnections	
sau khi ki Organize • Netw Realt	Ét nối thành côi → Control Panel → Network Disconnect this connection Ork cable unplugged H PCIe GBE Family Controlle PN Connection Status Teral Details TPV4 Connectivity: IPv6 Connectivity: IPv6 Connectivity: Duration:	ng and Internet Network (Rename this connect VPN Connect VPN Connect WAN Minipo UNAN Minipo Interne No network access Connecte 00:00:11	Connections ► tion View status of tion tion tr(PPTP) SZ Network Connection Property Connection Property Connection Physical Ad DHCP Enal DHCP Enal		Search Network Cor n >> reless Network Cor in Tin neros AR9485WB-EE Value Value VPN Connection No 10.0.0.2	onnections	
sau khi ki	Ét nối thành côi Control Panel → Network Disconnect this connection ork cable unplugged ek PCIe GBE Family Controlle PN Connection Status heral Details onnection IPv4 Connectivity: IPv6 Connectivity: Duration: Details	ng and Internet Network (Rename this connect VPN Connect VPN Connect VPN Connect WAN Minipo UN network access Connecte 00:00:1	Connections > tion View status of tion tion tri (PPTP) Network Connection Description Property Connection Description Physical Ad DHCP Enat IPv4 Addre IPv4 Subne	• 49 this connection Win Ath nection Details nection Details: specific DN dress soled ss t Mask	Search Network Cor n >> reless Network Cor n Tin neros AR9485WB-E Value VPN Connection No 10.0.0.2 255.255.255	onnections	
sau khi ki	Ét nối thành côi Control Panel → Network Disconnect this connection ork cable unplugged ek PCIe GBE Family Controlle PN Connection Status Peral Details onnection IPv4 Connectivity: IPv6 Connectivity: IPv6 Connectivity: Details Details	ng and Internet Network (Rename this connect VPN Connect VPN Connect VPN Connect No network access Connecte 00:00:1	Connections > tion View status of tion tion tion t S Network Conr t s d Property Connection Physical Ad DHCP Enat IPv4 Addree IPv4 Subne IPv4 Addree IPv4 Subne IPv4 Perfau IP	+ 47 (this connection view of the section Details nection Details: -specific DN dress oled ss t Mask t Gateway Sangers	Search Network Connection No 10.0.2 255.255.255.255 10.0.0.1	ionnections	
sau khi ki		ng and Internet Network of Rename this connect VPN Connect VPN Connect WAN Minipol Interne No network access Connecte 00:00:11	Connections > tion View status of tion tion tr t S Network Connection Property Connection Property Connection Physical Ad DHCP Enak IPv4 Addrest IPv4 Subne IPv4 DHS S	+ 47 this connection this connection Win Vie Ath nection Details specific DN dress oled ss t Mask t Gateway servers	Search Network Connection n >> reless Network Corn nTin heros AR9485WB-E Value VPN Connection No 10.0.2 255.255.255.255 10.0.0.1 8.8.8	onnections	
sau khi ki	Ét nối thành côi Control Panel Network Disconnect this connection ork cable unplugged R PCIe GBE Family Controlle PN Connection Status Teral Details onnection IPv4 Connectivity: IPv6 Connectivity: Media State: Duration: Details :tivity Sent —	ng and Internet Network (Rename this connect VPN Connect VPN Connect VPN Connect VPN Connect ON network access Connecte 00:00:1	Connections ► tion View status of tion tion tion tr (PPTP) SZ Network Conr Property Connection Description Physical Addres IPv4 Addres IPv4 Addres IPv4 ViINS d IPv4 WINS NetPICPS or IPv4 WINS	+ 47 (this connection wive view of the section Details expection Details: specific DN dress oled ss t Mask t Gateway Server ser Topio Ep	Search Network Connection n » reless Network Connection n Tin neros AR9485WB-EE Value VPN Connection No 10.0.0.2 255.255.255.255 10.0.0.1 8.8.8.8 Yes	onnections	
sau khi ki		ng and Internet Network (Rename this connect VPN Connect VPN Connect VPN Connect VPN Connect VPN Connect VPN Connect VPN Connect VPN Connect VPN Connect	Connections ► tion View status of tion tion tion tr (PPTP) SZ Network Conr Property Consection Property Consection Physical Ad DHCP Enat IPv4 Addres IPv4 Addres IPv4 Addres IPv4 WINS NetBIOS ov 7		Search Network Connection n >> reless Network Connection No 10.0.02 255.255.255 10.0.0.1 8.8.8.8 Yes	onnections	
sau khi ki	Ét nối thành côi Control Panel → Network Disconnect this connection Area Connection Ork cable unplugged k PCIe GBE Family Controlle PN Connection Status neral Details onnection IPv4 Connectivity: IPv6 Connectivity: IPv6 Connectivity: Details ctivity Sent — Bytes: 8,944 Compression: 0 9	ng and Internet Network (Rename this connect VPN Connect VPN Connect VPN Connect VPN Connect OURD (Interne No network access Connecte 00:00:11	Connections ► tion View status of tion tion tri (PPTP) SZ Network Connection Property Connection Description Physical Ad DHCP Enat IPv4 Addres IPv4 Addres IPv4 Addres IPv4 DNS S d IPv4 WINS NetBIOS ov 7 6		Search Network Cor n >> reless Network Cor in Tin neros AR9485WB-EE Value VPN Connection No 10.0.02 255.255.255.255 10.0.0.1 8.8.83 Yes	onnections	
sau khi ki		ng c and Internet Network (Rename this connect r VPN Connect VPN Connect VPN Connect VPN Connect O0:00:1 Interne No network access Connecte 00:00:1 Received 3 A 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	Connections ► tion View status of tion tion tr (PPTP)		Search Network Cor n >> reless Network Cor n Tin neros AR9485WB-E Value VPN Connection No 10.0.0.2 255.255.255 10.0.0.1 8.8.8.8 Yes	onnections	
sau khi ki	Ét nối thành côi Control Panel → Network Disconnect this connection ork cable unplugged ek PCIe GBE Family Controlle PN Connection Status neral Details onnection IPv4 Connectivity: IPv6 Connectivity: IPv6 Connectivity: IPv6 Connectivity: Duration: Details ctivity Sent — Bytes: 8,94: Compression: 0 9 Errors: 0	ng c and Internet Network (Rename this connect VPN Connect VPN Connect VPN Connect VPN Connect VPN Connect O0:00:1 Interne No network acces Connecte 00:00:1 Received 3 3 0 0 Diagnose	Connections > tion View status of tion tion tion t S Vetwork Connection t s d Property Connection d Physical Ad DHCP Enat IPv4 Addres IPv4 Subne IPv4 DNS S d IPv4 DNS S d IPv4 WINS NetBIOS ov 5 6 0		Search Network Connection No 10.0.2 255.255.255 10.0.0.1 8.8.8.8 Yes	onnections	
sau khi ki	Ét nối thành côi Control Panel → Network Disconnect this connection ork cable unplugged ek PCIe GBE Family Controlle PN Connection Status neral Details onnection IPv4 Connectivity: IPv6 Connectivity: IPv6 Connectivity: IPv6 Connectivity: Duration: Details Ctivity Sent — Bytes: 8,94: Compression: 0 9 Errors: 0	ng cand Internet Network (Rename this connect VPN Connect VPN Connect VPN Connect VPN Connect O0:00: 1	Connections ► tion View status of tion tion tion type type SZ Network Connection Property Connection Property Connection Physical Addres IPv4 Addres IPv4 Addres IPv4 DNS S d IPv4 WINS NetBIOS ov D	fy fy this connection this connection fy final final	Search Network Connection No 10.0.2 255.255.255 10.0.0.1 8.8.8.8 Yes	ionnections	